

Model Number:

Approvals:

Accessories:

Job:

Type:

### TECHNICAL SPECIFICATIONS

Input Voltage: 120/277V, 60Hz  
 Input Wattage: 8.0 watts  
 Emergency Operation: 90 minutes  
 Minimum Initial Illumination: (1) or (2) lamps 1450-3500 lumens  
 Weight: 8.7 lbs  
 Operating Temperature Range: 0°C – 50°C

### LAMPS OPERATED<sup>1</sup>

	Lamp	Wattage (1 Lamp)	Wattage (2 Lamps)
LINEAR	T5	8-54W	8-28W
	T8	17-215W	17-40W
	T10	17-215W	17-40W
	T12	17-215W	17-40W
	Circline	20-40W	20-40W
	U-Shape	20-40W	20-40W
CFL	4-Pin	13-42W	13-42W
	Long	18-55W	18-50W
	2-Pin	-	-



The XEB-30-B-LM Fluorescent Emergency Ballast allows the same fixture to be used for both normal and emergency operation when used in conjunction with an AC ballast. If used in an emergency only fixture, no AC ballast is necessary. In the event of a power failure, the XEB-30-B-LM instantly switches to the emergency mode and operates one or two of the existing lamps for 90 minutes. The unit contains a field replaceable NiCad battery, charger, and electronic circuit in a single can. The XEB-30-B-LM can be mounted remotely or on top of the fixture, and is U.L. Listed for factory installation or retrofit applications. The XEB-30-B-LM has a minimal initial output of 3000 lumens for one lamp.

### FEATURES

- U.L. Listed for factory or field installation
- Will cold start and operate all specified lamps
- Compatible with ECO/low mercury lamps
- Listed 90 minute emergency run time, 24 hour recharge time
- High temperature, maintenance-free, NiCad battery with 7-10 year life expectancy
- Includes test switch and charge indicator accessory kit
- Meets or exceeds all National Electrical Code and Life Safety Code Emergency Lighting Requirements
- Painted, steel case
- 120/277V dual primary, 60Hz input

### CASE DIMENSIONS

Length 16.3"  
 Width 5.5"  
 Height 1.7"

### WARRANTY

The Exitronix XEB-30-B-LM is warranted for five (5) years from date of purchase. Warranty covers only Exitronix emergency ballasts installed as directed, and used under normal conditions. Warranty does not cover physical damage, abuse, or acts of God.



SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

### CONFORMANCE TO CODES & STANDARDS

U.L. 924 listed for factory installations or field retrofit applications. Emergency illumination time exceeds the National Electric Code (NEC), Life Safety Code (NFPA-LSP), and U.L. 924 90 minute requirements.

### REMOTE MOUNTING

When battery packs are remote mounted, the remote distance cannot exceed 1/2 of the distance from ballast to lamp, as specified by the AC ballast manufacturer. The maximum allowable remote mounting distance is 50 ft. from the lamp.

<sup>1</sup> These ballasts may operate other lamp types, please consult factory for compatibility.