

Model Number:

Accessories:

Job:

Type:

Approvals:

The Sierra 1 is a single phase, on-line, double conversion, solid state inverter system utilizing patented ECM technology. Each system consists of a solid-state inverter, a temperature compensated rectifier/battery charger, a continuous duty static switch, an internal maintenance bypass switch, battery plant, status/control panel, and synchronizing circuitry. The Sierra 1 functions in conjunction with the existing building electrical system to provide high quality power conditioning, back-up power protection and distribution for lighting loads and other critical loads. The enclosure is a Nema 3R (outdoor) rain/weather resistant enclosure designed for outdoor environmental conditions.

Standard Power Level: 0.075, 0.1, 0.15, .02, 0.3, 0.35, 0.525, 0.7, 0.875, 1.05, 1.4, 2.0, 2.4, 2.6, 3.0, 3.4 3.8, 4.2, 4.7, 5.25, 7.0, 8.0, 10.0, 12.0, 14.0, 18.0 and 21.0KW

Input Voltage: 120, 208, 240, 277 or 480 VAC

Input Voltage Range: +10% -15%

Output Voltage: 120, 208, 277, 480, 120/240 or 120/277 VAC

Output Voltage Regulation: ±3% for all loads and battery discharge mode

Output Frequency Range: 60 Hz, ±1%

Output Wave Form: Sine-wave <5% @ 100% linear load

Crest Factor: 2.5:1 typical

Input Protection: Input Main Circuit Breaker

Output Protection: Output Main Circuit Breaker

Surge Protection: The unit will protect itself and the load against surges defined in ANSI/IEEE C62.45 category A/B

Battery: Sealed maintenance-free (AGM) lead calcium

Recharge Current: Conforms to UL924 standards

External Battery: Provision for hardware connection of external battery cabinets or DC source

Efficiency: ≥92% at 100% linear load

Audible Noise: <45dBA

Operating Temperature: -20°C to 50°C (-4°F to 122°F)

Storage Temperature: -30°C to 60°C (-22°F to 140°F)

Humidity: 5 - 100%, Non-condensing

Cabinet: NEMA 3R



SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

ORDERING INFORMATION Example: SIE1-7-120-277-RP-90

Series	Power Rating	Input Voltage ¹	Output Voltage ¹	Options	Run Time ³
SIE1	0.075 = 75W	120 = 120VAC	120 = 120VAC	ECM120/# ² = 120V Environmental Control Module / Qty	5 = 5 Min
	0.1 = 100W	208 = 208VAC	208 = 208VAC	ECM277/# ² = 277V Environmental Control Module / Qty	10 = 10 Min
	0.125 = 125W	240 = 240VAC	277 = 277VAC	NOF/V/# = Normally OFF Output Circuit / Voltage / Qty	15 = 15 Min
	0.2 = 200W	277 = 277VAC	480 = 480VAC	NOH/V/# = Normally OFF "Hold ON" / Voltage / Qty	20 = 20 Min
	0.3 = 300W	480 = 480VAC	120/240 = 120/240VAC	OCB/V/#/A = Output Circuit Breakers / Voltage / Qty / Amps	25 = 25 Min
	0.35 = 350W		120/277 = 120/277VAC	EPO = Emergency Power Off	30 = 30 Min
	0.525 = 525W			RP = Remote Indicator Panel	45 = 45 Min
	0.7 = 700W			SNMP = SNMP Card	60 = 60 Min
	0.875 = 875W			FCON = Form C Contacts	90 = 90 Min (Std)
	1.05 = 1.05KW			OST = Onsite Start-Up	120 = 120 Min
	1.4 = 1.4KW			IDB = Internal Dimmer Bypass	180 = 180 Min
	2.0 = 2.0KW			EMB = External Maintenance Bypass Switch	240 = 240 Min
	2.4 = 2.4KW			HE = Heat Exchanger	
	2.6 = 2.6KW			HTR = Heater	
	3.0 = 3.0KW			EW = Extended Warranty	
	3.4 = 3.4KW				
	3.8 = 3.8KW				
	4.2 = 4.2KW				
	4.7 = 4.7KW				
	5.25 = 5.25KW				
7.0 = 7.0KW					
8.0 = 8.0KW					
10.0 = 10.0KW					
12.0 = 12.0KW					
14.0 = 14.0KW					
18.0 = 18.0KW					
21.0 = 21.0KW					

Notes

¹ Consult factory for other voltages, may effect weight, size and number of cabinets

² One ECM is used per switching device or circuit

³ Consult factory for other run times

Series	Power Rating (KVA/KW)	Voltage (VAC)		UPS Cabinet Dimensions			Battery Cabinet Dimensions			Combined Weight (LBS)	BTU	Battery Type	Output Protection	Safety Approval
		Select Input	Select Output	W	H	D	W	H	D					
Sierra 1 Single Phase On-line Inverter	0.075KW	120 208 240 277 480	120 208 277 480 120/240 120/277	20"	24"	8"	Not Required			100	20.4	Sealed, maintenance free (AGM) lead calcium	Input and ouput circuit breakers standard	UL924 UL1778 NFPA101 NFPA70 NEC
	0.1KW			20"	24"	8"	Not Required			110	27.2			
	0.125KW			20"	24"	8"	Not Required			120	34			
	0.2KW			20"	24"	8"	Not Required			130	54.4			
	0.3KW			20"	24"	8"	Not Required			140	81.6			
	0.35KW			20"	24"	8"	Not Required			150	95.2			
	0.525KW			41"	44"	32"	Not Required			630	142.8			
	0.7			41"	44"	32"	Not Required			640	190.4			
	0.875			41"	44"	32"	Not Required			670	238			
	1.05			41"	44"	32"	Not Required			710	285.6			
	1.4			41"	44"	32"	Not Required			790	380.8			
	2.0			41"	44"	32"	Not Required			870	544			
	2.4			41"	44"	32"	Not Required			920	652.8			
	2.6			41"	44"	32"	Not Required			930	707.2			
	3.0			41"	44"	32"	Not Required			980	816			
	3.4			41"	44"	32"	Not Required			1030	924.8			
	3.8			41"	44"	32"	Not Required			1090	1033.6			
	4.2			41"	44"	32"	Not Required			1150	1142.4			
	4.7KW			41"	72"	32"	Not Required			1630	1278.4			
	5.25KW			41"	72"	32"	Not Required			1630	1428			
7.0KW	41"	72"	32"	Not Required			1880	1904						
8.0KW	41"	72"	32"	Not Required			1880	2176						
10.0KW	41"	72"	32"	Not Required			2250	2720						
12.0KW	41"	72"	32"	Not Required			2640	3264						
14.0KW	41"	72"	32"	41"	72"	32"	2945	3808						
18.0KW	41"	72"	32"	41"	72"	32"	4145	4896						
21.0KW	41"	72"	32"	41"	72"	32"	4555	5712						

POWER RATING

75 - 21,000 watt, single phase output unit uses the latest technology to provide the most advanced performance and reliability features

INPUT

120, 208, 240, 277 or 480 VAC

AC Input Characteristics

- Input Frequency: 60 Hz
- Power walk-in: 0 to 100% over a 10-second period
- Magnetizing Inrush Current: Less than nominal input current for less than one cycle
- Input Surge Protection: The Sierra 1 is equipped with standard input filter assembly will withstand surges per IEEE 587-1980/ANSI C62.41

OUTPUT

120, 208, 277, 480, 120/240 or 120/277 VAC

AC Output Characteristics

- True On-line design is $\geq 92\%$ efficient at 100% linear load
- Voltage Regulation: + 3% for no-load to full load and full 90 minute battery discharge mode
- Frequency: 60 Hz (+ 0.1Hz when free running).
- Voltage Distortion: Maximum 5% total (THD) @ 100% linear loads.
- Voltage Transient (Step Load) Response:
 - +/- 5% for 50% step load change
 - +/- 8% for 100% step load change
 - +/- 3% for loss or return of AC input power or manual transfer at full load
- Voltage Recovery Time: Return to within 3% of nominal value within 50 milliseconds
- Non-Linear Load Capability: Output voltage total harmonic distortion shall be less than 8% when connected to a 100% non-linear load with a crest factor not to exceed 2.5%
- Slew Rate: 1 Hz/second maximum
- Power Factor: Unity power factor
- Inverter Overload Capability:
 - 125% of rated load for 1 minute
 - 145% of rated load for 10 seconds
- Bypass Overload Capability: > 200% for one cycle; > 150% for 30 seconds

BATTERIES

The Sierra 1 module employs a valve regulated sealed lead calcium heavy-duty industrial battery, designed for auxiliary power service. The primary battery is furnished with an impact resistant plastic case and housed in matching battery cabinet. (Systems up to 12KW are self contained.)

- Protection against Deep Discharge and Self-Discharge: The Sierra 1 is equipped with a device designed to protect the battery against deep discharge depending on discharge conditions, with isolation of the battery by a circuit breaker. In particular, a monitoring device shall adjust the battery shutdown voltage as a function of a discharge coefficient to avoid excessive discharge
- Battery Self-Test: The battery monitoring system shall be to perform the following automatic functions:
 - Battery circuit check
 - Partial discharge test customer selectable (12KW and above)
- Sealed, maintenance-free, lead calcium (AGM) batteries
- 10 year prorated warranty
- Guardian Smart Battery Monitoring System is TEMPERATURE COMPENSATED maintaining maximum runtime and battery life
- Microprocessor controlled recharge and overcharge protection is standard

LAMPS AND LOADS

- Emergency power provides FULL LIGHT OUTPUT from all lamps and fixtures for the entire runtime
- Standard or LED Exits and other safety equipment
- Standard or electronic ballasts, dimming devices or panels, sensors and most control equipment
- Operates fluorescent, compact fluorescent, incandescent, quartz, LED and other lamp types

PROTECTION

- Provides overload, surge and undercurrent protection using the latest technology and Guardian Diagnostics to protect system performance and reliability
- Surge protection against load surges as defined in ANSI/IEEE C62.45 category A and B

CODES

- City of Chicago and New York approved
- Complies with the Buy American Act (Level 3)
- The Sierra 1 shall meet the requirements of the following standards:
 - IEEE 587-1980/ANSI C62.41 1980 Standards for Surge Withstand Ability
 - FCC rules and regulations of Part 15, Subpart J, Class A
 - Meets UL 1778, UL 924, Standards for Lighting Inverter Equipment
 - NEMA PE 1 (National Electrical Manufacturers Association) - Lighting Inverter Systems
 - NEMA 250 (National Electrical Manufacturers Association) – Enclosures for Electrical Equipment (1000 Volts Maximum)
 - NFPA 70 – National Electrical Code
 - ISO 9001
 - Occupational Safety & Health Administration (OSHA)

DIAGNOSTICS, MAINTENANCE AND ACCESSIBILITY

All Sierra 1 sub-assemblies, as well as the battery, shall be accessible from the front only. The Sierra 1 design provides maximum reliability and minimum MTTR (mean time to repair). The electronic Sierra 1 control and monitoring assembly is fully microprocessor based. The unit is repairable by replacing standard subassemblies.

- Guardian Diagnostics provides complete self diagnostic capabilities and LED Monitoring
 - Informative advanced display and alarms allow complete control of your emergency lighting environment
 - Automatically performs periodic self-tests ensuring a safely lighted environment *prior* to an emergency
 - Single point of testing instead of multiple testing points with battery packs

CABINET

- Modular design that enables flexible installation
- Enclosure: The Sierra 1 is housed in a freestanding enclosure. The mechanical structure of the unit is sufficiently strong and rigid to withstand handling and installation operations without risk. Access to Sierra 1 subassemblies is through the front only. The sheet-metal elements in the structure shall be protected against corrosion by a suitable treatment, such as zinc electroplating, powder coating, epoxy paint or an equivalent.
- Cable Access: The Sierra 1 allows for side, top and bottom entry cables.
- Ventilation and Heat Rejection: The Sierra 1 is designed specifically for forced air cooling. Air inlets are provided from the front, bottom of the Sierra 1 enclosure. Air exhaust is achieved from the top or side portions of the unit
- Systems up to 12KW are self contained; larger systems require external battery cabinet(s)

INSTALLATION

- Modular design allows easy installation in electrical closet or other convenient locations
- Phone assisted factory start-up standard for all systems
- Extended warranty available
- The Sierra 1 shall operate under the following environmental conditions:
 - Temperature:
 - Sierra 1 Module
 - Operating: -20°C to 50°C (-4°F to 122°F)
 - Non-Operating: -30°C to 60°C (-22°F to 140°F)
 - Batteries: 25°C (77°F)
 - Relative humidity (operating and storage): 5 to 100% non-condensing
 - Barometric Pressure:
 - Up to 1000 meters above sea level
 - Up to 2000 meters with ambient temperature less than 28°C
 - Up to 12,000 meters above sea level non operating
 - Audible Noise: 45dBA at 3 feet
 - Enclosure is Nema 3R outdoor completely sealed, includes heat exchanger for complete environmental control of electronics and batteries
- Site Testing and Start-Up – If selected, the inverter system will be checked, started and tested by a manufacturer's qualified field service engineer either by phone start-up (standard) or by optional onsite start up when performed by a factory technician

SPECIAL APPLICATIONS

- Barron offers numerous UL924 optional devices to meet unusual or difficult application parameters
- ECM – Eco-Control Module allows fixtures and lamps on the emergency circuit(s) to be operated by normal switching and/or dimming devices in NON-emergency conditions
- Dimming Panel Interface allows use with emergency lights controlled by common dimmer panel

DELIVERY, STORAGE, AND HANDLING

- All products will be packaged in a manner to prevent penetration by debris and to allow safe delivery by all modes of ground transportation and air transportation where specified
- Prior to shipping all products will be inspected at the factory for damage
- Equipment shall be protected against extreme temperature and humidity and shall be stored in a conditioned or protected environment
- Equipment containing batteries shall not be stored for a period exceeding three months without powering up the equipment for a period of eight hours to recharge the batteries

WARRANTY

- 1 year full warranty on system electronics
- Battery warranty 1 year with 9 years pro-rated
- System 1 year on-site warranty labor with phone assisted start-up
- 5 year power train warranty
- Maintenance contracts available

