

| | |
|---------------------------------------|-------------------------|
| Model Number: Accessories: Job: | Approvals: Type: |
|---------------------------------------|-------------------------|

TECHNICAL SPECIFICATIONS

Input Voltage: 120/277V, 60Hz
 Input Wattage: 4.5 watts
 Emergency Operation: 90 minutes
 Minimum Initial Illumination: (1) or (2) lamps 2300-3000 lumens
 Weight: 9.75 lbs
 Operating Temperature Range: 0°C – 50°C



LAMPS OPERATED¹

| | Lamp | Wattage (1 Lamp) | Wattage (2 Lamps) |
|----------------|-------------|------------------|-------------------|
| LINEAR | T5 | 8-28W | 8-28W |
| | T5HO | 39-54W | 39-54W |
| | T8 | 17-40W | 17-40W |
| | T10 | - | - |
| | T12 | 20-215W | 20-40W |
| CFL | 4-Pin | 13-26W | 13-26W |
| | 4-Pin Long | 18-50W | 18-50W |
| | 2-Pin | - | - |
| SPECIAL | T9 Circline | 20-40W | 20-40W |
| | T8 U-Bend | 32W | 32W |
| | T8 U-Bend | 34W | 34W |

The XEB-3000 Fluorescent Emergency Ballast allows the same fixture to be used for both normal and emergency operation. In the event of a power failure, the XEB-3000 switches to the emergency mode and operates one or two of the existing lamps for 90 minutes. The unit contains a battery, charger, and inverter circuit in a single can and is provided with 2 feet of 3/8" flex for wiring to the fixture. The unit is designed for installation next to or on top of the fixture. The XEB-3000 has an initial output of up to 3000 lumens for one or two lamps, and features lamp selector leads for optimizing light output for designated lamp types.

FEATURES

- UL & CUL Listed for factory or field installation
- Will cold start and operate all specified lamps
- Compatible with ECO/low mercury lamps
- Listed 90 minute emergency run time, 24 hour recharge time
- High temperature, maintenance-free, NiCad battery with 7-10 year life expectancy
- Selectable lamp leads for optimal light output for desired lamp type
- Includes test switch and charge indicator accessory kit
- Meets or exceeds all National Electrical Code and Life Safety Code Emergency Lighting Requirements
- Painted, steel case
- 120/277V dual primary, 60Hz input
- Optional damp location rating (DR)



SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

CASE DIMENSIONS

Length 16.3"
 Width 3.0"
 Height 3.0"
 Mounting Center 15.875"

WARRANTY

The Exitronix XEB-3000 is warranted for five (5) years from date of purchase. Warranty covers only Exitronix emergency ballasts installed as directed, and used under normal conditions. Warranty does not cover physical damage, abuse, or acts of God.

CONFORMANCE TO CODES AND STANDARDS

UL 924 listed for factory installations or field retrofit applications. Emergency illumination time exceeds the National Electric Code (NEC), Life Safety Code (NFPA-LSP), and UL 924 90 minute requirements.

REMOTE MOUNTING

When battery packs are remote mounted, the remote distance cannot exceed 1/2 of the distance from ballast to lamp, as specified by the AC ballast manufacturer. The maximum allowable remote mounting distance is 50 ft. from the lamp.

¹ These ballasts may operate other lamp types, please consult factory for compatibility.

AVERAGE LUMEN RATINGS

| LAMP | 1 LAMP | 2 LAMPS |
|------------------|---------------|----------------|
| F40 T12/ES | 2700 | 2675 |
| F96 T12 | 2850 | |
| F25 T8 | 2300 | 2600 |
| F28 T8 | 2700 | 2700 |
| F32 T8 | 3000 | 3000 |
| F96 T8 | 2950 | |
| 28W T5 | 2450 | |
| 54W HO T5 | 2700 | |
| 26W Compact | 1500 | |
| 42W Compact | 2900 | 3000 |
| 57W Compact | 2700 | |
| 70W Compact | 2800 | |
| 40W Long Compact | 2600 | |
| 50W Long Compact | 2500 | |
| 55W Long Compact | 2500 | |
| 55W Circline T5 | 2700 | |



800.533.3948 • www.barronltg.com