

Model Number: Accessories: Job:	Approvals:  Type:
---------------------------------------	-------------------------

**TECHNICAL SPECIFICATIONS**

Input Voltage: 120/277V, 60Hz  
 Input Wattage: 4.5 watts  
 Emergency Operation: 90 minutes  
 Minimum Initial Illumination: (2) lamps 2600-3000 lumens  
 Weight: 9.75 lbs  
 Operating Temperature Range: 0°C – 50°C

**LAMPS OPERATED<sup>1</sup>**

	Lamp	Wattage (2 Lamps)
<b>LINEAR</b>	T5	54W
	T8	28-32W
	T10	28-32W
	T12	40W
	U-Shape	-
<b>CFL</b>	4-Pin	26-57W
	Long	-
	2-Pin	-

**FEATURES**

- Parallel lamp operation
- U.L. Listed for factory or field installation
- Will cold start and operate all specified lamps
- Listed 90 minute emergency run time, 24 hour recharge time
- High temperature, maintenance-free, NiCad battery with 7-10 year life expectancy
- Includes test switch and charge indicator accessory kit
- Meets or exceeds all National Electrical Code and Life Safety Code Emergency Lighting Requirements
- Painted, steel case
- 120/277V dual primary, 60Hz input
- Time delay enhancement for compatibility with end-of-lamp-life circuitry
- Optional damp location rating (DR)

**CASE DIMENSIONS**

Length 16.375"  
 Width 3.0"  
 Height 3.0"  
 Mounting Center 15.875"

**WARRANTY**

The Exitronix XEB-30-PAR is warranted for five (5) years from date of purchase. Warranty covers only Exitronix emergency ballasts installed as directed, and used under normal conditions. Warranty does not cover physical damage, abuse, or acts of God.



The XEB-30-PAR Fluorescent Emergency Ballast allows the same fixture to be used for both normal and emergency operation. In the event of a power failure, the XEB-30-PAR switches to the emergency mode and operates two of the existing lamps in parallel for 90 minutes. The unit contains a battery, charger, and inverter circuit in a single can and is provided with 2' of 3/8" flex for wiring to the fixture. The XEB-30-PAR can be mounted next to or on top of the fixture, and is UL Listed for retrofit applications. The XEB-30-PAR has an initial output of up to 3000 lumens for two lamps and is compatible with all electronic or magnetic, series or parallel output, multi-lamp ballasts.



SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

**CONFORMANCE TO CODES & STANDARDS**

U.L. 924 listed for factory installations or field retrofit applications. Emergency illumination time exceeds the National Electric Code (NEC), Life Safety Code (NFPA-LSP), and U.L. 924 90 minute requirements.

**REMOTE MOUNTING**

When battery packs are remote mounted, the remote distance cannot exceed 1/2 of the distance from ballast to lamp, as specified by the AC ballast manufacturer. The maximum allowable remote mounting distance is 50 ft. from the lamp.

<sup>1</sup> These ballasts may operate other lamp types, please consult factory for compatibility.

**AVERAGE LUMEN RATINGS**

<b>LAMP</b>	<b>2 LAMPS</b>
F28 T8	2700
F32 T8	3000
F40 T12	2675
54W T5	2500
26W PL CF Quad 4 Pin	2600
32W PL CF Quad 4 Pin	2750
42W PL CF Quad 4 Pin	2800
57W PL CF Quad 4 Pin	2500



800.533.3948 • [www.barronltg.com](http://www.barronltg.com)