

MODR4/6 Series

Installation Instructions



IMPORTANT SAFEGUARDS READ AND FOLLOW ALL SAFETY INSTRUCTIONS.

When using electrical equipment, basic safety precautions should always be followed including the following:

- **DISCONNECT AC POWER SUPPLY BEFORE SERVICING.**
- Installation and servicing of this equipment should be performed by qualified service personnel only.
- Ensure that the electrical wiring conforms to the National Electrical Code NEC® and local regulations if applicable.
- The National Electrical Code NEC® does not permit cords to be concealed where damage to the cord's insulation may go unnoticed. To prevent fire damage, do not run cord behind walls, ceilings, soffits or cabinets where it may be inaccessible for examination. Cords should be visually examined periodically and immediately replaced when any damage is noted.
- Install this kit only in the luminaire that has the construction features and dimensions shown in the photographs and/or drawings and where the input rating of the retrofit kit does not exceed the input rating of the luminaire.
- To reduce the risk of fire, electric shock or injury to persons, do not make or alter any open holes in a wiring enclosure or in any electrical components during kit installation. Luminaires wiring, power supply, or other electrical parts may be damaged when drilling for installation of retrofit kit hardware. Inspect wiring and components for damage.
- To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.
- This retrofit kit is accepted as a component of a luminaire where the suitability of the combination shall be determined by authorities having jurisdiction. The installation guide does not supersede local or national regulations for electrical installations.
- Do not mount near gas or electrical heaters.
- Suitable for Damp Locations.
- Equipment should be mounted in locations and at heights where it will not be readily subjected to tampering by unauthorized personnel.
- The use of accessory equipment not recommended by the manufacturer may cause an unsafe condition.
- Any modification or use of non-original components will void the warranty and product liability.
- Do not use this equipment for other than intended use.

SAVE THESE INSTRUCTIONS!

Technical Support ■ (623) 580-8943 ■ technicalsupport@barronltg.com

MODR4/6 Series

Installation Instructions

Ceiling Mount Installation

1. Turn off the power before installation. Remove the existing fixture if applicable.
2. Select desired lamp color with the CCT switch on back of fixture before installation.
3. Screw the E26 socket adapter into the existing socket. (Fig. 1)
4. Connect the terminals from the E26 adapter to the fixture. (Fig. 2 and 5)
5. For 4" retrofit, push fixture into the can, ensuring that it is flush with the ceiling. (Fig. 3) For 6" retrofit, press spring clips together (Fig. 4), push fixture up into the can and release once in. Continue pushing until flush with the ceiling (Fig. 6)

Fixture Removal

1. With fingertips, pull down firmly on the trim ring until the fixture stops.
2. Squeeze the torsion springs together to remove the LED fixture.
3. Disconnect the fixture from the E26 socket adapter.
4. Unscrew the E26 socket adapter from the recessed can.

Dimming Information

This unit may operate on other dimmers that haven't been tested.
(Input 120V, 60Hz)

LEVITON: 6672, RNL06, IPL06, DSL06, 6674

LUTRON: TG-600PR-WH, S-600PR-WH, CTCL-153PDH-WH, TGCL-153PH-LA, SLV-600P-AL, DV-600PR-WH, SCL-153PH-WH, GT-600P, DVCL-153P, MSCL-OP153M, PD-6WCL, MACL-153M//MA-R

Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6

