



EXITRONIX
emergency lighting

barrontg.com



CHICAGO APPROVED STEEL LED EXIT SIGN

Approved for use in the City of Chicago.

UL 924 Listed for Damp Locations.

Ceiling, end or wall mounting.

Rugged 20 gauge steel construction.

CHEX Series

CITY OF CHICAGO APPROVED STEEL LED EXIT SIGN


The CHEX Series is approved for use in the City of Chicago and features durable steel construction, high-efficiency LED illumination and attractive styling for ceiling, end or wall mount applications. A full range of glass panels makes this series suitable for indoor applications.

FEATURES & BENEFITS

- Approved for use in the City of Chicago
- UL 924 Listed for Damp Locations
- Universal input voltage from 100VAC to 300VAC, 50/60Hz
- Includes all necessary hardware for ceiling, end or wall mounting
- Constructed of rugged 20 gauge steel with heat-tempered, impact-resistant translucent glass panels

SPECIFICATIONS

| | |
|-----------------|---|
| Illumination: | Long-life, high-intensity, white LEDs. |
| Construction: | 20 Gauge steel with a white powder coated finish. Glass faceplates are heat-tempered and impact-resistant with red silk-screened lettering on white finish. |
| Battery: | Maintenance-free NiCad battery. |
| Operating Temp: | 10°C to 40°C (50°F to 104°F) |
| Run Time: | UL Listed 90 minute emergency run time, 24 hour recharge time. |
| Input Voltage: | Universal input voltage - 100 to 300VAC, 50/60Hz |
| Legend: | Fully illuminated red 6" characters with 3/4" stroke. |
| Mounting: | Canopy included for ceiling or end mounting. Can also be wall mounted (single-face). |
| Finishes: | White |
| Certifications: | UL 924 Listed, meets or exceeds NEC requirements and NFPA 101, suitable for Damp Locations, City of Chicago approved. |
| Warranty: | Five years with a separate five year prorated warranty on the battery. See the full Exitronix warranty document for detailed information. |



ORDERING INFORMATION (Example: CHEX-WB-WH-3)

| Series | Power Source | Finish | Panel Code ¹ | Single-face Panel Accessories ³ | Double-face Panel Accessories ³ |
|---|-----------------------------------|------------|--------------------------------------|--|---|
| CHEX | LB = AC Only WB = With Battery | WH = White | Single-face 3 = EXIT ² | CHEX-PANEL-3 = EXIT ⁴ CHEX-PANEL-6 = EXIT ▶ CHEX-PANEL-9 = EXIT ◀ CHEX-PANEL-12 = EXIT ◀▶ CHEX-PANEL-2 = STAIRS CHEX-PANEL-5 = STAIRS ▶ CHEX-PANEL-8 = STAIRS ◀ | CHEX-PANEL-18 = EXIT CHEX-PANEL-21 = EXIT ◀ or ▶ CHEX-PANEL-24 = EXIT ◀▶ CHEX-PANEL-17 = STAIRS CHEX-PANEL-20 = STAIRS ◀ or ▶ |
| Notes | | | | | |
| ¹ All panels supplied with red letters on a white background | | | | | |
| ² Only "EXIT" panel conforms to UL Standards | | | | | |
| ³ Order as separate line item, field installed | | | | | |
| ⁴ One faceplate only | | | | | |

Specifications are subject to change without notice. Installation must be performed in accordance with Barron Lighting Group installation instructions.

10840345 MKT-LIT-CHEX Rev 3

BARRON
lighting group

7885 North Glen Harbor Blvd
Glendale, Arizona 85307
800.533.3948
barronlgt.com